

Coupe-circuit 1P+N pour cartouche cylindrique domestique 16A

REF. 0 058 21

LEGRAND

Produit de vente courante habituellement stockée par la distribution



CARACTÉRISTIQUES PRODUIT

Coupe-circuit domestique, pour cartouche cylindrique domestique

- Coupe-circuit unipolaire + Neutre pour cartouche cylindrique domestique 10,3x25,8mm - 16A - 1 module - Livré sans cartouche
- Couplage par peigne d'alimentation - Bornes à étriers capacité 2x10mm²
- Equipé de porte-étiquette
- A préhenseur isolé Classe II
- Conforme aux normes NF C 61-203, NF C 60-200-3, NF HD 60269-3, IEC 60269-3, NF EN 60269-1 et IEC 60269-1

Les + installation

Cadenassable

Les + utilisation

Possibilité de signalisation par voyant pour repérer la cartouche fondue

Recommandations / restrictions d'usages

This product should be installed in compliance with installation rules, preferably by a qualified electrician. Incorrect installation and/or incorrect use can lead to risk of electric shock or fire. Before carrying out the installation, read the instructions and take account of the product's specific mounting location. Do not open up, dismantle, alter or modify the device except where specifically required to do so by the instructions. All Legrand products must be opened and repaired exclusively by personnel trained and approved by Legrand. Any unauthorised opening or repair completely cancels all liabilities and the rights to replacement and guarantees. Use only Legrand brand accessories.

CARACTÉRISTIQUES TECHNIQUES

Tension nominale	250 V
Type de montage	rail DIN
Pour taille de fusible	autre
Nombre de pôles	1
Conducteur neutre branché simultanément	Oui
Classe de protection (IP)	IP20